


Thank you for showing your confidence in us by purchasing the BEHRINGER CHORUS SPACE-C CC300. This ultimate effects pedal comes with 4 dedicated space presets that let you add a breathtaking third dimension to your sound or instrument. Experience the secret weapon of professional recording studios.

The chorus effect adds a shifting detuned signal to the original, similar to playing in unison in a group of instruments, and it is often used for dispersing sounds.

1. CONTROLS




Top view

- 1 The *MODE SELECTOR* switches let you choose between 4 dedicated space presets. Use these presets in any combination or even activate them at the same time. This results in 16 combinations giving you a wide range of spacious effects. The effect gets deeper from the left to the right.
- 2 The *ON/BATT* LED illuminates when the effect is activated. It also serves as a battery level indicator.
- 3 Use the footswitch to activate/deactivate the effect.
- 4 Use this 1/4" TS *IN* connector to plug in the instrument cable.
- 5 The two 1/4" TS *OUT A* and *OUT B* connectors send the signal to your amp. Use both connectors if you want to achieve full stereo chorus effect. For mono use plug in *OUT A* only.

Use the *DC IN* connection to plug in a 9 V power supply (not included).

The *BATTERY COMPARTMENT* is located underneath the pedal cover. To install or replace the 9 V battery (not included), press the hinges with a ballpoint pen and remove the pedal cover. Be careful not to scratch the unit.

 **The CC300 has no on/off switch. As soon as you insert the plug into the *IN* connector, the CC300 is on. When not in use, remove the plug from the *IN* connector. This extends the life of the battery.**

The *SERIAL NUMBER* is located at the underside.

2. WARRANTY

For our current warranty terms, please refer to our website at <http://www.behringer.com>.

3. SPECIFICATIONS

In	Connector	1/4" TS
	Impedance	500 kΩ
Out A	Connector	1/4" TS
	Impedance	1 kΩ
Out B	Connector	1/4" TS
	Impedance	1 kΩ
Power supply		9 V $\overline{-}$, 100 mA, regulated BEHRINGER PSU-SB
	USA/Canada	120 V \sim , 60 Hz
	Europe/U.K./Australia	230 V \sim , 50 Hz
	China	220 V \sim , 50 Hz
	Korea	220 V \sim , 60 Hz
	Japan	100 V \sim , 50/60 Hz
Power connector		2 mm DC jack, negative center
Battery		9 V type 6LR61
Power consumption		30 mA
Dimensions (H x W x D)		approx. 54 mm (2 1/8") x 70 mm (2 3/4") x 123 mm (4 4/5")
Weight		approx. 0.33 kg (0.73 lbs)

BEHRINGER is constantly striving to maintain the highest professional standards. As a result of these efforts, modifications may be made from time to time to existing products without prior notice. Specifications and appearance may therefore differ from those listed or shown.

4. SAFETY INSTRUCTIONS

Do not use near water, or install near heat sources. Use only authorized attachments/accessories. Do not service product yourself. Contact our qualified servicing personnel for servicing or repairs, **especially when power supply cord or plug is damaged.**

No utilizar cerca de agua o instalar cerca de fuentes de calor. Utilice sólo accesorios y aditamentos autorizados. No intenté reparar el producto usted mismo. Contacte a nuestro personal técnico cualificado para servicio y reparaciones, **especialmente cuando la fuente o el cable de alimentación estén dañados.**

Не эксплуатируйте прибор вблизи от источников воды и тепла. Применяйте только авторизованные дополнительные устройства. Никогда не ремонтируйте прибор самостоятельно. Ремонт может производить только квалифицированный специализированный персонал, **особенно при повреждениях сетевого провода или сетевой вилки.**

水分の近くや、ヒーターなど熱気のある場所では使用しないでください。正式に認可された付属品のみを使用してください。製品はご自分では決して修理せず、特に電源コードもしくはプラグが損傷した場合には、必ず製品サービスおよびリペアの資格を有した当社の担当員にご相談ください。

不要在靠近水源的地方使用，或在靠近热源的地方安装。只使用经过许可的附件/配件。不要自己进行产品维修，**尤其是当电源线或插座损坏的时候**。请联系我们的专业服务人员有关产品维修事宜。

Die deutsche Anleitung ist erhältlich @ www.behringer.com

Manuel francophone en téléchargement sur www.behringer.com

Manual en español disponible en www.behringer.com

Manuali italiani disponibili @ www.behringer.com

Русскоязычное руководство @ www.behringer.com

Polska instrukcja dostępna jest pod adresem @ www.behringer.com

Nederlandse handleiding beschikbaar @ www.behringer.com

Suomenkielinen käyttöohje saatavilla osoitteesta www.behringer.com

Svensk manual finns tillgänglig på www.behringer.com

Dansk vejledning findes på @ www.behringer.com

Manual português disponível @ www.behringer.com

Ελληνικό εγχειρίδιο υπάρχει διαθέσιμο στη διεύθυνση www.behringer.com

日本語版マニュアル@ www.behringer.com

使用说明书可在 www.behringer.com 下载

Technical specifications and appearance subject to change without notice. The information contained herein is correct at the time of printing. BEHRINGER accepts no liability for any loss which may be suffered by any person who relies either wholly or in part upon any description, photograph or statement contained herein. Colours and specification may vary slightly from product. Products are sold through our authorised dealers only. Distributors and dealers are not agents of BEHRINGER and have absolutely no authority to bind BEHRINGER by any express or implied undertaking or representation. No part of this manual may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording of any kind, for any purpose, without the express written permission of BEHRINGER International GmbH. BEHRINGER, the BEHRINGER logo and JUST LISTEN are trademarks of BEHRINGER. ALL RIGHTS RESERVED. © 2006 BEHRINGER International GmbH, Hanns-Martin-Schleyer-Str. 36-38, 47877 Willich-Müncheide II, Germany. Tel. +49 2154 9206 0, Fax +49 2154 9206 4903